



CMCP-RM-8AI and CMCP-RM-16AI

Modbus RTU, RS-485 Analog to Digital Converter

Features:

- 16 bit A/D converter for precision measurements
- Smart filtering provides excellent noise rejection
- Isolation on the RS485 lines eliminates ground loops
- Field replaceable current shunts save maintenance time
- Field configurable wiring choice for loop-powered transmitters or ground return instru-



Specifications:

Number of channels	8 or 16
Input range	4-20 mA
A/D resolution	16 bits (0.003%)
Full scale accuracy (@20°C)	+/- 0.10%
Span and offset temp. coefficient	+/- 50 ppm per °C typical
Input impedance	100 Ohms
DMRR (differential rejection at 50/60 Hz)	66 dB
Input current protection	Replaceable shunts
Fastest scan rate	8 Channel - 500 mS 16 Channel - 1,000 mS
Required supply voltage	10-30 VDC (0.75 watt typical)
Operating temperature range	-30 to 70° C
Storage temperature range	-40 to 85° C
Humidity (non-condensing)	5 to 95%
RS485 isolation	1200 Volts RMS 1 minute

Ordering Information:

Part No.	Description
CMCP-RM-8AI	A to D Converter Modbus RTU, RS-485, 16 bit, 8 Channel
CMCP-RM-16AI	A to D Converter Modbus RTU, RS-485, 16 bit, 16 Channel
CMCP-RM-232-SETUP	Field Setup Module with RS-232 cable to connect to computer
CMCP-RM-232/485	Converter for RS-232 to RS-485

Your STI Representative:

Although care has been taken to assure the accuracy of the data compiled in this publication, Sales Technology, Inc. (STI) does not assume any liability for errors or omissions. STI reserves the right to alter any part of this publication without prior notice.

(5/3/01) Copyright © 1999-2001 by Sales Technology, Inc.

ALL RIGHTS RESERVED